



1 **EC TYPE-EXAMINATION CERTIFICATE**

2 Equipment intended for use in Potentially Explosive Atmospheres Directive 94/9/EC

3 Certificate Number: **Sira 09ATEX3286X** Issue: **2**

4 Equipment: **BExCP3A, BExCP3B, GNExCP6A and GNExCP6B Manual Call Points**

5 Applicant: **European Safety Systems Limited**

6 Address: **Impress House
Mansell Road
Acton
London W3 7QH
UK**

7 This equipment and any acceptable variation thereto is specified in the schedule to this certificate and the documents therein referred to.

8 Sira Certification Service, notified body number 0518 in accordance with Article 9 of Directive 94/9/EC of 23 March 1994, certifies that this equipment has been found to comply with the Essential Health and Safety Requirements relating to the design and construction of equipment intended for use in potentially explosive atmospheres given in Annex II to the Directive.

The examination and test results are recorded in the confidential reports listed in Section 14.2.

9 Compliance with the Essential Health and Safety Requirements, with the exception of those listed in the schedule to this certificate, has been assured by compliance with the following documents:

IEC 60079-0:2007 Ed 5 EN 60079-1:2004 EN 60079-7:2007 IEC 60079-18:2009 Ed 3
EN 61241-1:2004

10 If the sign 'X' is placed after the certificate number, it indicates that the equipment is subject to special conditions for safe use specified in the schedule to this certificate.

11 This EC type-examination certificate relates only to the design and construction of the specified equipment. If applicable, further requirements of this Directive apply to the manufacture and supply of this equipment.

12 The marking of the equipment shall include the following:



II 2GD

BExCP3A Call Points: Ex e d IIC T6 Gb (-40°C ≤ Ta ≤ +55°C)
Ex t IIIC T60°C Db (-40°C ≤ Ta ≤ +55°C)

BExCP3B Call Points: Ex e d mb IIC T4 Gb (-40°C ≤ Ta ≤ +50°C)
Ex t IIIC T70°C Db (-40°C ≤ Ta ≤ +50°C)

GNExCP6A Call Points: Ex e d IIC T6 Gb (-40°C ≤ Ta ≤ +55°C)
Ex t IIIC T60°C Db (-40°C ≤ Ta ≤ +55°C)

GNExCP6B Call Points: Ex e d mb IIC T4 Gb (-40°C ≤ Ta ≤ +50°C)
Ex t IIIC T80°C Db (-40°C ≤ Ta ≤ +50°C)

Project Number 25199

C Ellaby
Deputy Certification Manager

This certificate and its schedules may only be reproduced in its entirety and without change.

Sira Certification Service

Rake Lane, Eccleston, Chester, CH4 9JN, England



SCHEDULE

EC TYPE-EXAMINATION CERTIFICATE

Sira 09ATEX3286X
Issue 2

13 DESCRIPTION OF EQUIPMENT

The equipment is a range of manual call points, as described below:

Model	Description of enclosure	Mode of operation	Contents includes
BExCP3A-BG	Aluminium enclosure fitted with a glass window	Break glass	'Ex d' switch
BExCP3A-PB	Aluminium enclosure fitted with a push button	Push button fitted with a spring-loaded cover that must be lifted before operating	'Ex d' switch
BExCP3A-PT	Aluminium enclosure fitted with a push button	Push button fitted with a spring-loaded cover that must be lifted before operating, the push button can only be reset by a tool	'Ex d' switch
BExCP3B-BG	Aluminium enclosure fitted with a glass window	Break glass	'Ex d' switch and up to two resistor modules
BExCP3B-PB	Aluminium enclosure fitted with a push button	Push button fitted with a spring-loaded cover that must be lifted before operating	'Ex d' switch and up to two resistor modules
BExCP3B-PT	Aluminium enclosure fitted with a push button	Push button fitted with a spring-loaded cover that must be lifted before operating, the push button can only be reset by a tool	'Ex d' switch and up to two resistor modules

In all cases, external connections are made via 'Ex e' terminals mounted within the enclosure, the cables entering the enclosure via certified cable glands.

The following ratings are applicable:

BExCP3A Range of Call Points	BExCP3B Range of Call Points
AC Voltage 250 V Max Current 5 A Max DC Voltage 50 V Max Current 1 A Max	DC Voltage 56 V Max Current 0.75 A Max or DC Voltage 28 V Max Current 1.0 A Max or DC Voltage 15 V Max Current 1.0 A Max or DC Voltage 9 V Max Current 1.0 A Max



SCHEDULE

EC TYPE-EXAMINATION CERTIFICATE

Sira 09ATEX3286X
Issue 2

Variation 1 - This variation introduced the following changes:

- i. The option to use of an alternative type of terminal in the BExCP3A-BG, BExCP3A-PB, BExCP3A-PT, BExCP3B-BG, BExCP3B-PB and BExCP3B-PT Manual Call points.
- ii. The introduction of type GNEXP6A-BG, GNEXP6A-PB, GNEXP6A-PT, GNEXP6B-BG, GNEXP6B-PB and GNEXP6B-PT Manual Call Points; these utilise a plastic enclosure and house an extended range of optional modules.

Model	Description of enclosure	Mode of operation	Contents includes
GNEXP6A-BG	Plastic enclosure fitted with a glass window	Break glass	'Ex d' switch (S) – up to two
GNEXP6A-PB	Plastic enclosure fitted with a push button	Push button fitted with a spring-loaded cover that must be lifted before operating	
GNEXP6A-PT	Plastic enclosure fitted with a push button	Push button fitted with a spring-loaded cover that must be lifted before operating, the push button can only be reset by a tool	
GNEXP6B-BG	Plastic enclosure fitted with a glass window	Break glass	'Ex d' switch (S) – up to two And up to two of the following: Resistor Module Diode Module Zener Diode Module Or one of the following: Resistor Module Diode Module Zener Diode Module With one: LED Indicator Assembly
GNEXP6B-PB	Plastic enclosure fitted with a push button	Push button fitted with a spring-loaded cover that must be lifted before operating	
GNEXP6B-PT	Plastic enclosure fitted with a push button	Push button fitted with a spring-loaded cover that must be lifted before operating, the push button can only be reset by a tool	

In all cases, external connections are made via 'Ex e' terminals mounted within the enclosure, the cables entering the enclosure via certified cable glands.

The following ratings are applicable:

GNEXP6A Range of Call Points	GNEXP6B range of Call Points
AC Voltage 250 V Max Current 5 A Max DC Voltage 50 V Max Current 1 A Max	Voltage # V DC Max Current # A Max (# Due to the large number of options, it is not practical to detail a full list of available values, therefore, the manufacturer marks the actual figures applicable to each specific device on the product label in accordance with their drawings.)



SCHEDULE

EC TYPE-EXAMINATION CERTIFICATE

Sira 09ATEX3286X
Issue 2

14 DESCRIPTIVE DOCUMENTS

14.1 Drawings

Refer to Certificate Annexe.

14.2 Associated Sira Reports and Certificate History

Issue	Date	Report no.	Comment
0	9 December 2009	R18381A	The release of the prime certificate.
1	19 December 2011	R25199A/00	The introduction of Variation 1.
2	17 February 2012	R25199A/01	Report no. R25199A/01 replaced R25199A/00.

15 SPECIAL CONDITIONS FOR SAFE USE (denoted by X after the certificate number)

15.1 The terminals shall be fitted only with wires that have cross-sectional area falling within the following limitations:

BExCP3A and GNExCP6A Call Points fitted with Weidmuller terminal strip; 0.5 mm² to 4 mm²
BExCP3A and GNExCP6A Call Points fitted with Phoenix terminal strip; 0.2 mm² to 4 mm²
BExCP3B and GNExCP6B Call Points fitted with Weidmuller terminal strip; 0.5 mm² to 4 mm²
BExCP3B and GNExCP6B Call Points fitted with Phoenix terminal strip; 0.2 mm² to 4 mm²
BExCP3B and GNExCP6B Call Points fitted with Weidmuller rail mounted terminals; 0.5 mm² to 2.5 mm²

15.2 The following apply to the Call Points fitted with Weidmuller Terminals:

- Not more than one single or multiple strand lead shall be connected to a terminal, unless multiple conductors have been joined in a suitable manner, e.g. two conductors into a single insulated crimped boot lace ferrule.
- Leads connected to the terminals shall be insulated for the appropriate voltage and this insulation shall extend to within 1mm of the metal of the terminal throat.
- During installation, the terminals shall be only wired with cable in an ambient temperature range between -10°C to 80°C.

15.3 The following apply to the Call Points fitted with Phoenix Terminals:

- The number of conductors per clamping shall be either 1 conductor per clamping unit, 0.2 – 4 mm² or 2 conductors with the same cross section and the same conductor type 0.2 – 1.5 mm². If 2 conductors are fitted in one clamping unit they may be joined in a suitable manner, e.g. two conductors into a single insulated crimped boot lace ferrule.

15.4 All terminal screws, used or unused, shall be fully tightened down.

15.5 The GNExCP6 Call Points are supplied with M20 threaded entries, the BExCP3 Call Points have plain, M20 holes. All of these shall be fitted with either a cable gland or certified blanking element that is suitable for the application and has been certified by a notified body. These shall provide and maintain a minimum enclosure ingress protection of IP66.

15.6 For GNExCP6B Call Points that have a maximum rated current marked, the prospective short-circuit current of the circuit connected shall be limited to the marked rated current.

15.7 The enclosure of the GNExCP6 Call Points is non-conducting and may generate an ignition-capable level of electrostatic charges under certain extreme conditions. The user should ensure that the equipment is not installed in a location where it may be subjected to external conditions (such as high-pressure steam) which might cause a build-up of electrostatic charges on non-conducting surfaces. Additionally, cleaning of the equipment should be done only with a damp cloth.

This certificate and its schedules may only be reproduced in its entirety and without change.

Sira Certification Service

Rake Lane, Eccleston, Chester, CH4 9JN, England

Tel: +44 (0) 1244 670900

Fax: +44 (0) 1244 681330

Email: info@siracertification.com

Web: www.siracertification.com



SCHEDULE

EC TYPE-EXAMINATION CERTIFICATE

Sira 09ATEX3286X
Issue 2

16 ESSENTIAL HEALTH AND SAFETY REQUIREMENTS OF ANNEX II (EHSRs)

The relevant EHSRs that are not addressed by the standards listed in this certificate have been identified and individually assessed in the reports listed in Section 14.2.

17 CONDITIONS OF CERTIFICATION

- 17.1 The use of this certificate is subject to the Regulations Applicable to Holders of Sira Certificates.
- 17.2 Holders of EC type-examination certificates are required to comply with the production control requirements defined in Article 8 of directive 94/9/EC.
- 17.3 All complete BExCP3B-BG, BExCP3B-PB and BExCP3B-PT manufactured units shall be subjected to a routine dielectric strength test of 500V r.m.s. a.c. applied for 1 s or 600V r.m.s. a.c. applied for 100 ms between all terminals and the equipment enclosure, in accordance with Clause 9.2 of IEC 60079-18:2009.
- 17.4 All completed resistor modules, diode modules, zener diode modules and LED indicator encapsulated assemblies shall be subjected to a visual inspection on the encapsulation in accordance with Clause 9.1 of IEC 60079-18:2009. No damage shall be evident such as cracks in the compound, exposure of the encapsulated parts, flaking, inadmissible shrinkage, swelling, decomposition, failure in adhesion or softening.
- 17.5 The products covered by this certificate incorporate previously certified devices, it is therefore the responsibility of the manufacturer to continually monitor the status of the certification associated with these devices, and the manufacturer shall inform Sira of any modifications of the devices that may impinge upon the explosion safety design of their products.

Certificate Annexe

Certificate Number: Sira 09ATEX3286X
Equipment: BExCP3A, BExCP3B, GNECP6A and GNECP6B Manual Call Points
Applicant: European Safety Systems



Issue 0

Drawing	Sheets	Rev	Date (Sira stamp)	Title
D150-00-001-SC	1 of 1	C	08 Dec 09	BExCP3A-BG & BExCP3B-BG Manual Call Point Assembly
D150-00-001-CD-SC	1 of 1	A	08 Dec 09	BExCP3-XX and BExCP3-XX Call Point Circuit Operation Diagram
D150-00-101-SC	1 of 1	B	08 Dec 09	BExCP3-PB & BExCP3B-PB Manual Call Point Assembly
D150-00-201-SC	1 of 1	B	08 Dec 09	BExCP3-PT & BExCP3B-PT Manual Call Point Assembly
D150-10-900-SC	1 of 1	B	09 Dec 09	BExCP3B/PB/PT Call Point Resistor Potting Drawing
D150-99-001-SC	1 of 1	C	08 Dec 09	BExCP3A and BExCP3B Label Drawings

Issue 1

Drawing	Sheets	Rev	Date (Sira stamp)	Title
D150-00-001-SC	1 of 1	D	22 Dec 11	BExCP3A-BG & BExCP3B-BG Manual Call Point Assembly
D150-00-101-SC	1 of 1	C	22 Dec 11	BExCP3A-PB & BExCP3B-PB manual Call Point Assembly
D150-00-201-SC	1 of 1	C	22 Dec 11	BExCP3A-PT & BExCP3B-PT Manual Call Point Assembly
D154-00-001-SC	1 of 1	B	22 Dec 11	GNECP6A-BG & GNECP6B-BG & -PB -PT Manual Call Point Assembly
D154-00-101-SC	1 of 1	A	22 Dec 11	GNECP6A-PB & GNECP6B-PB Manual Call Point Assembly
D154-00-201-SC	1 of 1	A	22 Dec 11	GNECP6A-PT & GNECP6B-PT Manual Call Point Assembly
D154-00-001-CD-SC	1 of 1	B	22 Dec 11	GNECP6A-XX and BExCP6B-XX Call Point Circuit Operation Diagram
D154-10-910-SC	1 of 1	A	22 Dec 11	GNECP6B & BExCP3B – BG/PB/PT Call Point Diode Potting Drawings
D154-10-920-SC	1 of 1	A	22 Dec 11	GNECP6B & BExCP3B – BG/PB/PT Call Point Zener Diode Potting
D154-10-930-SC	1 of 1	B	22 Dec 11	GNECP6B-BG/PB/PT Call Point LED & Resistor Potting
D154-99-001-SC	1 of 1	C	22 Dec 11	BExCP6A and BExCP6B Label Drawings

Issue 2 (No new drawings were introduced.)

This certificate and its schedules may only be reproduced in its entirety and without change.